

# FX-PCV1832 N2 Programmable VAV Box Controller Catalog Page

Code No. LIT-1900783  
 Software Release 6.0  
 Issued January 30, 2013

Refer to the [QuickLIT website](#) for the most up-to-date version of this document.

The FX-PC Series N2 Programmable Controller family comprises a group of versatile controllers and accessories designed to monitor and operate a wide variety of commercial HVAC equipment and can be networked together using the N2 Open Communications protocol. This family of controllers includes the FX-PCV1832 N2 Programmable VAV box controllers, which can be integrated to any supervisory controller capable of managing N2 Open networks and devices, such as an FX Supervisory Controller.

The FX-PCV1832 controller features an advanced design that provides optimum performance and easy access to power, network, and field terminations. These controllers come with 32-bit microprocessors that meet and exceed ever-demanding industry standards.

**Note:** A software download that allows FX-PCV1832 controllers to communicate as BACnet® Master-Slave/Token-Passing (MS/TP) devices will be available at a future date. This functionality provides a differentiated and cost-effective platform upgrade path for existing customers who are looking for a gradual upgrade strategy and should be considered during installation of the controller.

Our wide variety of network sensor models provides options for measuring and displaying zone temperature, occupancy detection, duct temperature, zone humidity, carbon dioxide (CO<sub>2</sub>) level, setpoint adjustments, and discharge air temperatures. The FX-PCV1832 controller's embedded capabilities, in addition to its modular accessories, make it well-suited as a replacement for legacy VMA14xx Series Controllers.

Refer to the *FX-PC Series N2 Programmable Controllers and Related Products Product Bulletin (LIT-12011809)* for important product application information.

## Features

- N2 Open Communications Protocol
- Standard Software Platform
- Auto Tuned Control Loops
- Universal Inputs and Binary and Configurable Outputs
- Optional Local Controller Display/Keypad (FX-DIS1710)

If the FX-PCV1832 fails to operate within its specifications, replace the unit. For a replacement FX-PC controller, contact the nearest Johnson Controls® representative.

Figure 1: FX-PCV1832 Controller

## Selection Charts

Table 1: FX-PCV1832 Features and Point Type Counts per Model

Point Types	Signals Accepted	FX-PCV1832
Modular Jack		8-pin SA bus supports analog non-communicating sensor.
Universal Input (UI)	Analog Input, Voltage Mode, 0–10 VDC Analog Input, Resistive Mode, 0–2k ohm, RTD (1k NI [Johnson Controls], 1k PT, A998 SI), NTC (10k Type L, 2.252k Type 2) Binary Input, Dry Contact Maintained Mode	3
Binary Output (BO)	24 VAC Triac	3
Configurable Output (CO)	Analog Output, Voltage Mode, 0–10 VDC Binary Output Mode, 24 VAC Triac	2
Integrated Actuator	Internal	1
Integrated Flow Sensor	Internal	1

**Table 1: FX-PCV1832 Features and Point Type Counts per Model**

Point Types	Signals Accepted	FX-PCV1832
Zone Sensor Input	On SA Bus <sup>1</sup>	Up to 4 NS Series Network Zone sensors Up to 5 FX-WRZ sensors when using the one-to-one FX-WRZ78xx wireless configuration.

1 A total of 10 SA bus addresses maximum can be used in a single FX-PCV1832 controller.

**Table 2: Ordering Information**

Product Code Number	Description
FX-PCV1832-0	Programmable VAV Box Controller featuring integrated actuator and pressure sensor, 8 onboard I/Os (3 UI, 3 BO, and 2 CO), SA Bus, and N2 Open Communication protocol

**Accessories (Order Separately)**

**Table 3: FX-PCV1832 Controller Accessories**


Product Code Number	Description
Y64T15-0	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 92 VA, Foot Mount, 30 in. Primary Leads and 30 in. Secondary Leads, Class 2
Y65A13-0	Transformer, 120 VAC Primary to 24 VAC Secondary, 40 VA, Foot Mount (Y65AS), 8 in. Primary Leads and 30 in. Secondary Leads, Class 2
Y65T42-0	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 40 VA, Hub Mount (Y65SP+), 8 in. Primary Leads and Secondary Screw Terminals, Class 2
Y65T31-0	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 40 VA, Foot Mount (Y65AR+), 8 in. Primary Leads and Secondary Screw Terminals, Class 2
AS-CBLVMA-1	Cable Adapter, 8-pin Female Socket to 6-Pin Male Jack (Bulk Pack of 10)
AP-TBK4FC-0	Replacement MS/TP FC Bus Terminal, 4-Position Connector, Blue, Bulk Pack (10 pack)
AP-TBK1002-0	Removable 2-Position Screw Terminal Kit (100 Pieces)
AP-TBK1003-0	Removable 3-Position Screw Terminal Kit (100 Pieces)
AS-CBLVMA-2	Cable Adapter, 8-pin Female Socket to 8-pin Male Jack with 6-Pin Female Socket for Wireless Commissioning Converter (Bulk Pack of 10)
FX-BTCVT-1	Wireless Commissioning Converter with Bluetooth® Technology
FX-DIS1710-0	Local Controller Display/Keypad
NS-WALLPLATE-0	Network Sensor Wall Plate (80 mm by 80 mm [3.15 in. by 3.15 in.] square), used with an 80 mm by 80 mm (3.15 in. by 3.15 in.) network sensor and must be mounted to a 0.6 m by 1.2 m (2 ft by 4 ft) wall box
NS Series Network Sensors	Refer to the <i>NS Series Network Sensors Product Bulletin (LIT-12011574)</i> for specific sensor model descriptions.

**Technical Specifications**

**Table 4: FX-PCV1832 Controllers**

Product Code Numbers	FX-PCV1832-0: Programmable VAV Box N2 Controller for cooling only and cooling with reheat and fan control applications
Supply Voltage	24 VAC (nominal, 20 VAC minimum/30 VAC maximum), 50/60 Hz, Power Supply Class 2 (North America), Safety Extra-Low Voltage (SELV) (Europe)
Power Consumption	10 VA typical, 14 VA maximum  <b>Note:</b> The VA ratings do not include any power supplied to the peripheral devices connected to Binary Outputs (BOs) or Configurable Outputs (COs), which can consume up to 12 VA for each BO or CO, for a possible total consumption of an additional 60 VA (maximum).
Ambient Conditions	<b>Operating:</b> 0 to 50°C (32 to 122°F) <b>Storage:</b> -40 to 70°C (-40 to 158°F)
Terminations	Inputs/Outputs, SA bus, and Supply Power: 6.3 mm (1/4 in.) Spade Lugs N2/FC Bus Pluggable Screw Terminal Block TSTAT Modular Port: RJ-45 8-Pin Modular Jack
Controller Addressing	DIP switch set  <b>N2 Open Protocol:</b> Valid field controller device addresses 1–253 <b>BACnet MS/TP:</b> Valid field controller device addresses 4–127 (Device addresses 0–3 and 128–255 are reserved and not valid field controller addresses.)

**Table 4: FX-PCV1832 Controllers**

<b>Communications Bus</b>	<p><b>N2 Open Protocol:</b> N2/FC Bus: 1.5 mm (18 AWG) standard 3-wire, twisted, shielded cable recommended between the supervisory controller and field controllers</p> <p><b>BACnet MS/TP Protocol:</b> SA Bus: 0.6 mm (22 AWG) stranded, 4-wire (2-twisted pairs) shielded cable recommended from the FX-PCV controller for network sensors and other sensor/actuator devices; includes a terminal to source 15 VDC supply power from FX-PCV to SA Bus devices<sup>1</sup></p>
<b>Input and Output Capabilities</b>	<p>3 - Universal Inputs: Defined as 0–10 VDC, 4–20 mA, 0–600k ohm, or Binary Dry Contact</p> <p>3 - Binary Outputs: Defined as 24 VAC Triac (internal power source)</p> <p>2 - Configurable Outputs: Defined as 0–10 VDC or 24 VAC Triac BO</p>
<b>Analog Input/Analog Output Accuracy</b>	<p><b>Analog Input:</b> 15-bit resolution on UIs</p> <p><b>Analog Output:</b> 0–10 VDC ± 200 mV</p>
<b>Differential Pressure Sensor</b>	<p>Range: -1.5 inches to 1.5 inches H<sub>2</sub>O</p> <p><b>Performance Characteristics:</b> Total Error Band: ±1.3% Full Span Maximum Accuracy: ±0.25% Full Scale Best Fit</p>
<b>Actuator Rating</b>	4 N·m (35 lb·in) minimum shaft length = 44 mm (1-3/4 in.)
<b>Mounting</b>	Mounts to damper shaft using single set screw and to duct with single mounting screw
<b>Dimensions</b> (Height x Width x Depth)	165 x 125 x 73 mm (6.5 x 4.92 x 2.9 in.) <b>Center of Output Hub to Center of Captive Spacer:</b> 135 mm (5-5/16 in.)
<b>Weight</b>	0.65 kg (1.45 lb)
<p><b>Compliance</b></p> 	<p><b>United States:</b> UL Listed, File E107041, CCN PAZX, UL 916, Energy Management Equipment; Suitable for use in other environmental air space (plenums) in accordance with Section 300.22(C) of the National Electric Code. FCC Compliant to CFR47, Part 15, Subpart B, Class A.</p> <p><b>Canada:</b> UL Listed, File E107041, CCN PAZX7, CAN/GSA C22.2 No. 205, Signal Equipment; Industry Canada Compliant, ICES-003</p> <p><b>Europe:</b> CE Mark – Johnson Controls, Inc., declares that this product is in compliance with the essential requirements and other relevant provisions of the EMC Directive 2004/108/EC.</p> <p><b>Australia and New Zealand:</b> C-Tick Mark, Australia/NZ Emissions Compliant.</p>

<sup>1</sup> For more information, refer to the *N2 Communications Bus Technical Bulletin (LIT-636018)*.



**Building Efficiency**  
507 E. Michigan Street, Milwaukee, WI 53202

*Johnson Controls® is a registered trademark of Johnson Controls, Inc.  
All other marks herein are the marks of their respective owners. © 2013 Johnson Controls, Inc.*